

Betriebsdaten:

Typical operation:

Exemple d'utilisation:

U_f . . . 7,5 V=
 I_f . . . 1,25 A
 U_a . . . +425 V=
 U_g . . . -40 V=
 I_a 18 mA
 S 1,6 mA/V
 D 12,5 %
 g 8
 R_i 5 k Ω
 R_a 10,2 k Ω

Prüfdaten:

Test operation:

Vérification:

U_f . . . 7,3 V~
 U_a . . . +150 V=
 U_g . 0 & -2 V=

In Stellung 13
auf Steuerwirkung
prüfen

In position 13 is to
prove the control grid.
En position 13 vérifier
l'action de commande de la
grille.

571

Patent-Röhrenprüfer Modell W 19

MAX FUNKE, Adenau-Eifel 2. 55.


**Grenzdaten:**

Ratings: / Conditions maxima:

P . . . 1,6 W

10	202	310	L 10	801	VT-25
10 S	210	410	PT 210	801 A	VT-62
10 Y	210 T	2100	RK 10	H 801 A	

Triode.



Unbrauchbar
mauvais / Bad

?

G u t
Good / Bon

