



Betriebsdaten:

Typical operation:

Exemple d'utilisation:

U_f . . . 6.3 V
 I_f . . . 0.6 A
 U_a . . . +250 V=
 U_{g1} . . . 0
 I_a . . . 5.3 mA
 R_{aa} . . . 14 k Ω

Grenzdaten:

Ratings: / Conditions maxima:

\mathcal{P} . . . 2.24 W
 U_{fk} . . . 90 V

Prüfdaten:

Test operation:

Vérification:

U_f . . . 6.3 V~
 U_a . . . +150 V=
 U_{g1} . . . 0 & -2 V=

In Stellung 13
auf Steuerwirkung
prüfen

In position 13 is to
prove the control grid.
En position 13 vérifier
l'action de commande de la
grille.

579

Patent-Röhrenprüfer Modell W19

MAX FUNKE, Adenau-Eifel 3. 55



79
179
VT-79

Triode + Triode
Karte 579 + Karte 580

Unbrauchbar
mauvais / Bad

?

G u t
Good / Bon



5 mA