



Betriebsdaten:

Typical operation:

Exemple d'utilisation:

U_f 20 V
 I_f 0,18 A
 U_a . . . +200 V=
 U_{g1} . . . -18 V=
 I_a 15 mA
 S 2,5 mA/V
 D 16,7 %
 g 6
 R_i 4 k Ω
 R_a 16 k Ω
 R_k 1,2 k Ω

Grenzdaten:

Ratings: / Conditions maxima:

N_a 5 W
 N 0,2 W

Prüfdaten:

Test operation:

Vérification:

U_f 20 V~
 U_a . . . +150 V=
 U_{g1} . 0 & -2 V=

In Stellung 13
auf Steuerwirkung
prüfen

In position 13 is to
prove the control grid.
En position 13 vérifier
l'action de commande de la
grille.

Patent-Röhrenprüfer Modell W 19

MAX FUNKE, Adenau-Eifel 3, 55.

Telefunken REN 1822	Valvo L 2218	Tungsram P 2018 d	Philips B 2006
Triode.			
Unbrauchbar mauvais / Bad	?	G u t Good / Bon	➔

