

↑  
AS 242  
RS 242

**Betriebsdaten:**  
Typical operation:  
Exemple d'utilisation:

$U_f$  . . . 3,8 V  
 $I_f$  . . . 0,65 A  
 $U_a$  . max 300 V=  
 $I_a$  . . . 80 mA  
 $S$  . . . . 4 mA/V  
 $D$  . . . . 6 %  
 $g$  . . . . 17  
 $N_a$  . . . 15 W  
 $N$  . . . 12 W

**Prüfdaten:**  
Test operation:  
Vérification:

$U_f$  . . . 4 V~  
 $U_a$  . . +200 V=  
 $U_g$  . 0 & -2 V=

In Stellung 13  
auf Steuerwirkung  
prüfen

In position 13 is to  
prove the control grid.  
En position 13 vérifier  
l'action de commande de la  
grille.

1300

Patent-Röhrenprüfer Modell W19

MAX FUNKE, Adenau-Eifel 3. 54.

**AS 242**  
AS 242 spez.




**RS 242**  
RS 242 spez.

Triode.

Unbrauchbar  
mauvais / Bad

?

**G u t**  
Good / Bon



← AS 442 spez.  
RS 442 spez.