




Betriebsdaten:
Typical operation:
Exemple d'utilisation:

U_f . . . 10 V=
 I_f . . . 2 A
 U_a . . +160 V=
 U_g . . +160 V=
 I_a . . 400 mA
 S . . . 2,6 mA/V
 D . . . 4,5 %
 g . . . 22

Grenzdaten:
Ratings: / Conditions maxima:

U_a . . +1000 V=
 I_k . . 100 mA
 N_a . . 40 W
 N . . 60 W



Prüfdaten:
Test operation:
Vérification:

U_f . . . 10 V~
 U_a . . +200 V=
 U_g . . 0 & -2 V=

In Stellung 13
auf Steuerwirkung

prüfen
 In position 13 is to
 prove the control grid.
 En position 13 vérifier
 l'action de commande de la
 grille.

273

Patent-Röhrenprüfer Modell W19

MAX FUNKE, Adenau-Eifel 2. 55.

RS 276

RS 276 II

Triode.

Unbrauchbar
 mauvais / Bad

?

G u t
 Good / Bon

