

Betriebsdaten:

Typical operation:

Exemple d'utilisation:

U_f . . . 2,2 V=
 I_f . . . 1,1 A
 U_a . . +350 V=
 U_g . . -10 V=
 I_a . . . 6 mA
 S . . . 0,6 mA/V
 D . . . 7 %
 g . . . 14
 R_i . . 25 k Ω

Grenzdaten:

Ratings / Conditions maxima:

U_a . . +350 V=
 N_a . . . 2 W

**Prüfdaten:**

Test operation:

Vérification:

U_f . . . 2,0 V~
 U_a . . +200 V=
 U_g . 0 & -2 V=

In Stellung 13
auf Steuerwirkung
prüfen

In position 13 is to
prove the control grid.
En position 13 vérifier
l'action de commande de la
grille.

1304

Patent-Röhrenprüfer Modell W19

MAX FUNKE, Adenau-Eifel 9. 54.

RV 322
RV 322 spez.

Triode.

Unbrauchbar
mauvais / Bad

?

G u t
Good / Bon

